

## Wi-Fi Smart Dimmer Switch, 150W LED / 600W Incandescent, Neutral Wire Required

### OVERVIEW

The C-PAC-SM150-L is a Wi-Fi-enabled smart dimmer switch designed for single-pole residential and light commercial installations. It controls dimmable LED and CFL loads up to 150W and incandescent or halogen loads up to 600W at 120VAC/60Hz. The switch integrates with the Tuya SmartLife app (Android and iOS) and supports voice control via Amazon Alexa and Google Home, along with scheduling functionality. A neutral wire is required for installation, and operation requires a 2.4 GHz Wi-Fi network.

The housing is constructed from UL94 V0-rated flame-classified thermoplastic. Rated operating temperature ranges from -20°C to 60°C, and the switch is rated for 40,000 switching cycles. The LED/CFL dimming circuit is rated at 2A or 150W maximum.

This product carries cETLus certification and is tested to UL 1472 and CSA C22.2 No.184.1-15.

### SPECIFICATIONS

<b>Power</b>	600 W	<b>Weight</b>	72 g
<b>Input voltage</b>	120VAC 60Hz	<b>Operating temp</b>	-20 to 60 °C
<b>Dimensions</b>	116 x 70.2 x 41 mm		

### DRAWING



### CERTIFICATIONS & COMPLIANCE



ETL Listed