

Combo Red LED Exit Sign with Adjustable Head Lights and 90-Minute Battery Backup

OVERVIEW

The EM-EBS2x1-R-UL is a combination red LED exit sign with integrated adjustable emergency head lights, designed for commercial and industrial indoor applications requiring both egress signage and supplemental emergency illumination from a single unit. The fixture supports ceiling and wall mounting configurations and connects to standard junction boxes.

The unit operates on 120/277VAC dual-voltage input and delivers up to 3W maximum output. It is equipped with a sealed lead-acid battery rated at 3.6V/800mAh, providing greater than 90 minutes of emergency backup duration. The exit sign face uses 12 red LEDs. The fixture measures approximately 11.73" x 7.36" in face dimensions. Rated for indoor use only.

This product is UL Listed. Installation must be performed by qualified personnel in accordance with applicable local electrical codes and ordinances. Battery should be charged for a minimum of 24 hours upon initial connection before relying on emergency backup operation.

SPECIFICATIONS

Power	1–2 W	Dimensions	11.73 x 7.36 x 1.77 in
Input voltage	120/277 VAC		

DIMENSION

