



Fixing Channel for M-N11 Flexible Neon Rope Light, 8.2 ft (2.5 m)

- Length of 8.2 ft (2.5 m) per channel section
- Integrated slot accepts M-N11 flexible neon rope light directly
- Rated for use with rope light LED lifetime of 50,000 h
- Suitable for indoor and outdoor mounting applications
- Backed by a 1-year warranty

OVERVIEW

The M-N11-Ch-8 is a fixing channel designed specifically for the M-N11 Flexible Neon Rope Light. At 8.2 ft (2.5 m) in length, it provides a dedicated mounting solution for securing and routing the rope light in commercial, industrial, and residential installations. The integrated slot accepts the M-N11 rope light directly, producing a clean, finished appearance suitable for both indoor and outdoor applications.

The channel supports straightforward installation — the rope light slides into the slot and seats securely without additional hardware. The design also allows for routine maintenance, including cleaning and rope light replacement, without removing the entire mounting assembly.

SPECIFICATIONS

OPTICAL

LED Lifetime 50,000 h

MECHANICAL

Length 2.5 m
8.2 ft

ORDERING

Warranty 1 y

APPLICATIONS

- Commercial signage edging
- Outdoor architectural trim
- Residential accent lighting mounts
- Industrial fixture channels

PROVENANCE — REVIEW COPY ONLY

slug	value	source	confidence
led_lifetime_h	50,000 h	db	high
length	2.5 m	pdf	high
warranty_years	1 y	db	high

Specifications subject to change without notice.